

## FarSite Communications Cable Connector Pin Allocations

### FarSync M1P QCX1 R02 (X.21) Cable – Product Code FS6086

#### For use with FarSync M-Series M1P v2 cards

The label on the cable must read: **QCX1 R02**

The cable assembly shall comprise a length of cable with PC-Card I/O Cable Plug (A3 LAN CLOSED SYSTEM KEY) fitted to one end of the cable, and a DB15 plug connector fitted to the other end of the cable.

The connections required are defined in the table below:

Interface Signal Name	DB15 Plug Contact	PC-Card I/O Plug Contact	Twisted Pairs
ATXa / TXDA	2	15	PAIR
ATXb	9	14	
ASa / TXCA	6	13	PAIR
ASb	13	12	
ARXa / RXDA	4	11	PAIR
ARXb	11	10	
ASVa / Ala	5	9	PAIR
ASVb / Alb	12	8	
ACa / RTSA	3	7	PAIR
ACb	10	6	
GNDA	8	1	
SHIELD	Hood + Shell	Shield	