

FarSite Communications Cable Connection Pinouts

FarSync TE1 MCE1 R00 Cable

For use with FarSync T-Series TE1 cards

The label on the cable must read: **MCE1 R00**

The cable assembly shall comprise a length of Cat.5 UTP cable with an RJ48 plug (same as RJ45 but with different pin allocations) at each end of the cable.

The overall length of the cable assembly shall be 2.0 metres (+/- 0.05m)

The connections required are defined in the table below:

Interface Signal Name	RJ48 #1	RJ48 #2
TX Tip	5	5
TX Ring	4	4
RX Tip	2	2
RX Ring	1	1

Contacts 3, 6, 7, 8 on each RJ48 plug are not used.